

Photonis 0387 HSB MRTS Anode Software User Manual	 Micro-Key Embedded Technology Experts	
Description: User manual for HSB module repair test set	Doc No.:	PHO-0387-S2-2-0
	Revision:	003
	Date:	22-11-2017

* The approval box may be extended as necessary.

	Name	Date	Signature
Author	M. Mitscherlich	22-11-2017	
Reviewed			
Approved			

No part of this document may be reproduced in any form or by any means, without the prior written permission of the respective owners.
All trademarks are property of their respective owners.



Document History

Version	Date	Status	Description
001	01-09-2017	draft	Initial draft
002	07-09-2017	draft	Updates after review by KRe and GRo
003	22-11-2017	draft	Updates after review by Photonis Updates after spec additions

Table of Contents

1	INTRODUCTION.....	4
1.1	SCOPE.....	4
1.2	REFERENCES	4
1.3	DEFINITIONS.....	4
2	SYSTEM OVERVIEW.....	5
2.1	DISPLAY.....	5
2.2	KEYPAD	6
3	SERVICE MANUAL.....	7
3.1	SELECTION CURSOR	7
3.2	START SCREEN.....	8
3.3	MAIN MENU	9
3.3.1	<i>Tesla repair - Tube repair menu</i>	10
3.3.1.1	Select preset menu.....	10
3.3.1.2	Preset preview screen	10
3.3.1.3	Start repair menu	11
3.3.1.3.1	Error messages based on safety.....	11
3.3.1.3.2	Repair in progress.....	11
3.3.1.4	Repair pause	12
3.3.1.4.1	Repair paused.....	12
3.4	ADMINISTRATOR MENU	13
3.4.1	<i>Password protection</i>	13
3.4.1.1	Password insertion screen.....	13
3.4.1.2	Password accepted.....	13
3.4.1.3	Password denied	13
3.4.2	<i>Operator main menu</i>	14
3.4.2.1	Change PIN menu	15
3.4.2.1.1	Insert new Pin	15
3.4.2.1.2	New Pin OK	15
3.4.2.1.3	New Pin failed	16
3.4.2.2	I/O control menu	17
3.4.2.2.1	Read interlock	18
3.4.2.2.2	Solenoids	19
3.4.2.2.3	Get voltage in	20
3.4.2.2.4	Teslagun relais.....	22
3.4.2.2.5		23
3.4.2.3	Information and version screen.....	23
3.5	CALIBRATION MENU	24
3.5.1	<i>Password protection</i>	24
3.5.1.1	Password insertion screen.....	24
3.5.1.2	Password accepted.....	24
3.5.1.3	Password denied	24
3.5.2	<i>Calibration main menu</i>	25
3.5.2.1	Calibrate ADCs menu	25
3.5.2.1.1	Calibration procedure for an ADC channel.....	26



1 Introduction

1.1 Scope

This document describes the end-user functionality of the Photonis HSB module repair test set. It gives detailed overview over the menu structure and explains the interactivity between user and device.

1.2 References

- [1] Document somename, vvv
Micro-Key, dd-mm-yyyy

1.3 Definitions

TBD To Be Defined

2 System overview

Interaction between user and system occurs via two devices which are part of the HSB module repair test set.

2.1 Display

Visual feedback and information is provided to the user through a display. It contains four rows with 20 characters each.



Figure 1: New heaven display NHD-0420D3Z-FL-GBW-V3

Within this document the display content is related to by a table. Below represents the display seen from left to right and up to down as a matrix of 4x20.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3																				
4																				

As example, the table below represents the same display content as in *Figure 1*.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	S	c	h	e	d	u	l	e	:		M	o	n	.	-		F	r	i	.
2	O	p	t	i	o	n	s		P	r	e	s	e	t	:		A	2	1	
3	A	u	t	o	-	o	f	f	:		N	O								
4	A	c	c	e	s	s	:		P	u	b	l	i	c						

2.2 Keypad

The system contains a keypad which represents the only possibility for the user to interact with the several functions of the system.



Figure 2: 16-key keypad

The keypad consists of a matrix of four by four keys, making it 16 keys totally. They are labelled as follows:

0-9	Numeric keys 0 - 9
←	Arrow left
↑	Arrow up
→	Arrow right
↓	Arrow down
ENT	Enter
X	Escape

3 Service manual

3.1 Selection cursor

As soon as a menu with selectable items appears on the display there must be a cursor/selector to differ between the currently highlighted menu item and other items.

The cursor is character: >

The cursor is always in first position of the current row, followed by a blank (space character).

For example, the cursor active in third row with random text behind looks like:

/	1	2	3	4
1	R	a	n	d
2			1	.
3	>		2	.
4			3	.

3.2 Start screen

After powering the system, the display will become active and print out a start message, containing the type of assemblage and version number.

For tesla repair repair set:

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	T	e	s	l	a		r	e	p	a	i	r								

A full start message on display, containing the system version number, will look like:

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	T	e	s	l	a		r	e	p	a	i	r								
2																				
3					S	W		U	.		1	.	0	.	0	.	0			
4																				

There is no user-action needed at this point – the system will switch to the main menu as soon as the system is fully booted and functional.

3.3 Main menu

After booting, the system switches to the main menu.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	T	e	s	l	a		r	e	p	a	i	r								
2	>		1	.	T	u	b	e		r	e	p	a	i	r					
3			2	.	A	d	m	i	n	i	s	t	r	a	t	o	r			
4			3	.	C	a	l	i	b	r	a	t	i	o	n					

Note: The item 2 and 3 are PIN protected.

1-3	Select item 1-3 respectively
↑	Move cursor up one line
↓	Move cursor down one line
ENT	Select currently current item
others	No function

3.3.1 Tesla repair - Tube repair menu

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	T	u	b	e		r	e	p	a	i	r									
2	>		1	.	S	e	l	e	c	t		P	r	e	s	e	t			
3			2	.	S	t	a	r	t											
4																				

1-2	Select item 1-2 respectively
↑	Move cursor up one line
↓	Move cursor down one line
ENT	Select currently current item
X	Leave current menu level and return to main menu
others	No function

3.3.1.1 Select preset menu

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	S	e	l	e	c	t		P	r	e	s	e	t							
2	>		1	.	P	r	e	s	e	t		1								
3			2	.	P	r	e	s	e	t		2								
4			3	.	P	r	e	s	e	t		3								

The screen continues to item "9.Preset 9".

1-9	Select item 1-9 respectively and return to tube repair menu
↑	Move cursor up one line
↓	Move cursor down one line
→	Go to preset preview menu of the current currently under the cursor
ENT	Select preset currently under the cursor and return to tube repair menu
X	Leave current menu level and return to tube repair menu without selecting a (new) voltage
others	No function

3.3.1.2 Preset preview screen

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	P	r	e	s	e	t		X		i	n	f	o							
2	S	t	a	r	t	:				1	2	3	m				1	2	3	m
3	T	i	m	e	:					1	2	3	m				1	2	3	m
4	V	o	l	t	:			1	2	3	4	5	m		1	2	3	4	5	m

Where 'X' is the number of the preset that has been selected for preview.

←	Go back select preset menu
X	Go back select preset menu
others	No function

3.3.1.3 Start repair menu

3.3.1.3.1 Error messages based on safety

Before starting the repair treatment, it will be verified that the cover of the drawer is closed correctly. For safety reason the cover must be closed before the repair treatment can be started.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1						!	!	E	R	R	O	R	!	!						
2					C	O	V	E	R		O	P	E	N						
3																				
4			H	i	t		X		t	o		c	o	n	t	i	n	u	e	

X	Acknowledge error and return to main menu
others	No function

Note: it is not sufficient to close the cover. The system will only react to the X key and return to the main menu. Closing the cover is, however, mandatory before starting a new repair.

3.3.1.3.2 Repair in progress

When all conditions are met, the repair treatment starts. The display now acts as feedback

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	X			h	h	:	m	m	:	s	s		t	o	t	a	l			
2				h	h	:	m	m	:	s	s		r	e	m	a	i	n		
3										R	2									
4									1	2	3	4	U							

The number in row1/column1 represents the selected preset number.

X	Pause the current repair action
others	No function

3.3.1.4 Repair pause

3.3.1.4.1 Repair paused

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2						R	E	P	A	I	R		B	U	S	Y				
3			H	i	t			X			t	o		P	A	U	S	E		
4																				

When X is hit during an active repair, the screen above appears. This is to suppress accidental keyboard actions. If a pause is requested the user must press X a second time. This screen will remain on display for one second. If the X-button is not pressed within this time, the system will return to the “repair in progress” screen.

X	Pause the current repair action
others	No function

Pausing the repair process automatically turns down the voltage output of all rows to 0 volts. It can take some time to unload all capacities on the rows, so the system will keep waiting until all rows have a voltage below the safety threshold. The display will notify about this waiting time with the following screen

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3					W	A	I	T	I	N	G		F	O	R					
4						P	O	W	E	R		D	O	W	N					

When treatment is paused, the display will change its output to:

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2						!	!	P	A	U	S	E	!	!						
3		H	i	t		E	N	T		t	o		c	o	n	t	i	n	u	e
4		H	i	t			X			t	o		R	E	S	E	T			

ENT	Continue the current repair
X	Reset/quit the treatment and return to the tube repair menu
others	No function

3.4 Administrator Menu

3.4.1 Password protection

3.4.1.1 Password insertion screen

The operator menu is password protected. Prior to entering, the user must enter the password.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3						I	n	s	e	r	t		P	I	N					
4									-	-	-	-								

0-9	Insert number
←	Backspace – delete last entered digit
ENT	Confirm inserted PIN
X	Return to main menu
others	No function

3.4.1.2 Password accepted

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3								P	I	N		O	K							
4																				

others	No function
--------	-------------

No action required. The screen will be left after three seconds and the operator menu will be entered.

3.4.1.3 Password denied

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3						P	I	N		D	E	N	I	E	D					
4																				

others	No function
--------	-------------

No action required. The screen will be left after one second and the system will return to the main menu.

3.4.2 Operator main menu

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	A	d	m	i	n	i	s	t	r	a	t	i	o	n						
2	>		1	.	C	h	a	n	g	e		P	I	N						
3			2	.	I	/	O		c	o	n	t	r	o	l					
4			3	.	P	r	e	s	e	t		c	o	n	f	i	g			

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
			4	.	P	I	D		c	o	n	s	t	a	n	t	S			
			5	.	I	n	f	o		&		U	e	r	s	i	o	n		

1-5	Select item 1-5 respectively
↑	Move cursor up one line
↓	Move cursor down one line
ENT	Select currently current item
X	Leave current menu level and return to main menu
others	No function

3.4.2.1 Change PIN menu

3.4.2.1.1 Insert new Pin

/		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	h	a	n	g	e		P	I	N											
2																					
3		I	n	s	e	r	t		n	e	w		P	I	N	:		-	-	-	-
4																					

X	Leave current menu level and return to operator main menu without changing the PIN
←	Backspace – delete last entered digit
ENT	Confirm inserted PIN
0-9	Insert number
others	No function

When the 4-digit PIN has been entered, the screen automatically changes to:

/		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	h	a	n	g	e		P	I	N											
2																					
3					N	e	w		P	I	N	:				*	*	*	*		
4		R	e	p	e	a	t		P	I	N	:				-	-	-	-		

X	Leave current menu level and return to administrator main menu without changing the PIN
←	Backspace – delete last entered digit
ENT	Confirm inserted PIN
0-9	Insert number
others	No function

When the 4-digit has been entered a second time, the system will verify that both entered PINs are equal.

3.4.2.1.2 New Pin OK

/		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																					
2																					
3			N	e	w		P	I	N		a	c	c	e	p	t	e	d			
4																					

others	No function
--------	-------------

No action required. The screen will be left after three seconds and the administrator main menu will appear again.

3.4.2.1.3 New Pin failed

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3				N	e	w		P	I	N		d	e	n	i	e	d			
4																				

others	No function
--------	-------------

No action required. The screen will be left after three seconds and the administrator main menu will appear again.

3.4.2.2 I/O control menu

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	I	/	0		c	o	n	t	r	o	l									
2	>		1	.	R	e	a	d		i	n	t	e	r	l	o	c	k		
3			2	.	S	o	l	e	n	o	i	d	S							
4			3	.	G	e	t		v	o	l	t	a	g	e		i	n		

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
			4	.	S	e	t		v	o	l	t	a	g	e		o	u	t	
			5	.	T	e	s	l	a	g	u	n		r	e	l	a	i	s	

1-5	Select item 1-5 respectively
↑	Move cursor up one line
↓	Move cursor down one line
ENT	Select currently current item
X	Leave current menu level and return to operator menu
others	No function

3.4.2.2.1 Read interlock

Reading the interlock status is a constant action, meaning that the screen will immediately update its content with the interlock status.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2		C	O	V	E	R		I	N	T	E	R	L	O	C	K		I	S	
3																				
4																				

If interlock is open:

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
3									O	P	E	N								

If interlock is closed:

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
3								C	L	O	S	E	D							

X	Leave current menu level and return to operator menu
others	No function

3.4.2.2.2 Solenoids

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	S	o	l	e	n	o	i	d	s											
2			H	o	l	d		0		t	o		t	o	g	g	l	e		
3																				
4																				

0	Press: activate solenoids (open cover) Release: de-activate solenoids (seal cover)
X	Leave current menu level and return to administrator menu
others	No function

3.4.2.2.3 Get voltage in

The screen to read the voltage input is a read-only screen, meaning that no user action is accepted (other than leaving the menu).

The screen shows the currently read voltage on all three rows in both voltage (left value) and the corresponding hexadecimal value of the DA converter.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	G	e	t		v	o	l	t	a	g	e		i	n						
2																				
3	R	o	w	2	:			1	2	3	4	U	!		A	B	C	D	x	
4																				

X	Leave screen and return to administrator I/O menu
others	No function

Set voltage out

The screen to set the voltage input is allows to apply a voltage to the three rows.

The screen shows two values per row. The left value is the value that the administrator inserts and applies to the DA converter of that specific row. The right value of that row is the actual value that is read back from the AD converter of that same row.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	G	e	t		v	o	l	t	a	g	e		i	n						
2																				
3	R	o	w	2	:			1	2	3	4	U	!			1	2	3	4	U
4																				

0-9	Used for value insertion
←	Backspace – delete last entered digit
ENT	Accept inserted value and apply to DA converter of that row
X	Leave screen and return to administrator I/O menu
others	No function

Leaving the set voltage out menu causes the following screen to appear.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1																				
2																				
3	A	l	l		r	o	w	s		r	e	s	e	t		t	o		0	U
4		P	r	e	s	s		X		t	o		c	o	n	t	i	n	u	e

X	Leave screen and return to administrator I/O menu
others	No function

3.4.2.2.4 Teslagun relais

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	T	e	s	l	a	g	u	n		r	e	l	a	i	s					
2			H	o	l	d		Ø		t	o		t	o	g	g	l	e		
3																				
4																				

0	Press: activate relais Release: de-activate relais
X	Leave current menu level and return to administrator menu
others	No function

3.4.2.2.5

3.4.2.3 Information and version screen

The full screen on display, containing the system version number, will look like:

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	T	e	s	l	a		r	e	p	a	i	r								
2																				
3					S	W		U	.		1	.	0	.	0	.	0			
4																				

X	Leave screen and return to administrator menu
others	No function

3.5 Calibration menu

3.5.1 Password protection

3.5.1.1 Password insertion screen

The calibration menu is password protected. Prior to entering, the user must enter the password.

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1			C	a	l	i	b	r	a	t	i	o	n		m	e	n	u		
2																				
3						I	n	s	e	r	t		P	I	N					
4									-	-	-	-								

0-9	Insert number
←	Backspace – delete last entered digit
ENT	Confirm inserted PIN
X	Return to main menu
others	No function

3.5.1.2 Password accepted

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1			C	a	l	i	b	r	a	t	i	o	n		m	e	n	u		
2																				
3								P	I	N		O	K							
4																				

others	No function
--------	-------------

No action required. The screen will be left after 3 seconds and the calibration main menu will be entered.

3.5.1.3 Password denied

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1			C	a	l	i	b	r	a	t	i	o	n		m	e	n	u		
2																				
3						P	I	N		D	E	N	I	E	D					
4																				

others	No function
--------	-------------

No action required. The screen will be left after 3 seconds and the password insertion screen will appear again.

3.5.2 Calibration main menu

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	a	l	i	b	r	a	t	i	o	n		m	e	n	u				
2	>		1	.		C	a	l	i	b	r	a	t	e		A	D	C	s	
3																				
4																				

↑	Move cursor up one line (currently not implemented)
↓	Move cursor down one line (currently not implemented)
ENT	Select currently current item
X	Leave current menu level and return to main menu
others	No function

The only calibration option at the moment is the analogue-to-digital converter, or analogue input.

3.5.2.1 Calibrate ADCs menu

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	a	l	i	b	r	a	t	e		A	D	C	s						
2	>		1	.		C	h	a	n	n	e	l	1							
3			2	.		C	h	a	n	n	e	l	2							
4			3	.		C	h	a	n	n	e	l	3							

↑	Move cursor up one line
↓	Move cursor down one line
ENT	Select currently current item
X	Leave current menu level and return to main menu
others	No function

3.5.2.1.1 Calibration procedure for an ADC channel

The following menu is similar for all ADC channels

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	a	l	i	b	r	a	t	e		A	D	C		#	1				
2							P	r	o	v	i	d	e							
3										0		k	U							
4					a	n	d		h	i	t		E	N	T					

ENT	Confirm provided voltage and continue to next calibration point
X	Leave calibration procedure and return to calibrate ADCs menu
others	No function

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	a	l	i	b	r	a	t	e		A	D	C		#	1				
2							P	r	o	v	i	d	e							
3										1		k	U							
4					a	n	d		h	i	t		E	N	T					

ENT	Confirm provided voltage and continue to next calibration point
X	Leave calibration procedure and return to calibrate ADCs menu
others	No function

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	a	l	i	b	r	a	t	e		A	D	C		#	1				
2							P	r	o	v	i	d	e							
3										1	0		k	U						
4					a	n	d		h	i	t		E	N	T					

ENT	Confirm provided voltage and continue to next calibration point
X	Leave calibration procedure and return to calibrate ADCs menu
others	No function

/	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
1	C	a	l	i	b	r	a	t	e		A	D	C		#	1				
2					C	a	l	i	b	r	a	t	i	o	n					
3							f	i	n	i	s	h	e	d						
4																				

ENT	Confirm and return to calibrate ADCs menu
others	No function

The exact calibration procedure is not defined, yet, so the menu definition, especially the calibration points mentioned, are subject to changes!